



**Comments on: "Continuous initial observability of
nonlinear delay parabolic equations" by Choi, Kwung
and Park**

Rabah Rabah

► **To cite this version:**

Rabah Rabah. Comments on: "Continuous initial observability of nonlinear delay parabolic equations" by Choi, Kwung and Park. Far East Journal of Applied Mathematics, 2004, 15 (1), pp.113-115. hal-01091525

HAL Id: hal-01091525

<https://hal.science/hal-01091525>

Submitted on 5 Dec 2014

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Public Domain

Comments on: “Continuous initial observability
of nonlinear delay parabolic equations” by Rong
Jae Choi, Young Chel Kwun and Jong Seo Park

Rabah Rabah
IRCCyN UMR 6597,
1 rue de la Noë, BP 92101,
44321 Nantes Cedex 3, France
Email: rabah@emn.fr

Abstract. It is shown that the assumptions of the main result of the cited paper can never be satisfied.

Mathematical Subject Classification: 93C20, 93B07.

In the paper [1] the problem of continuous initial observability is considered for the delayed infinite dimensional system

$$\begin{cases} x(t) &= S(t)\phi(0) + \int_0^t S(t-s)F(s, x_s)ds, & t \in [0, T], \\ x(t) &= \phi(t), & t \in [-h, 0], \\ y(t) &= \Pi x(t), \end{cases} \quad (1)$$

where $S(t)$ is a C_0 -semigroup given on a Hilbert space, namely $X = L_2(\Omega)$, where Ω is a bounded domain in \mathbb{R}^n , Π is a bounded linear operator from X to the Hilbert space Y , F is a non linear function. In order to investigate this problem, authors consider the linear non delayed part of the system:

$$\begin{cases} \dot{x}(t) &= Ax(t) \\ x(0) &= \phi(0) \\ y(t) &= \Pi x(t). \end{cases} \quad (2)$$

The main assumptions are: the semigroup $S(t)$ is analytical and compact (assumption H3) and the system (2) is initially continuously observable (assumption H1). Under those assumptions conditions of initial continuous observability of the system (1) are given.

We claim that the necessary condition of initial continuous observability of the system (2) is that the semigroup $S^*(t)$ is onto or that each operator $S(t)$ has a bounded inverse operator defined on $\text{Im } S(t)$. If $S(t)$ is compact, then $S^*(t)$ is compact and cannot be onto in an infinite dimensional Hilbert space. If $S(t)$ is analytical then $\text{Im } S^*(t) \subset \mathcal{D}(A^*)$ and then the operators $S^*(t)$ cannot be onto.

We need a precise definition of the initial observability because the definition given in [1] is not clear. We refer to [2, 3, 4].

Definition 1 *Let H be the operator defined by:*

$$H : X \rightarrow L_2(0, T; Y), \quad (Hx)(t) = \Pi x(t) = \Pi S(t)\phi(0).$$

The system (2) is said initially observable if $\ker H = \{0\}$, that is the left inverse H^{-1} exists. It is said continuously initially observable if H^{-1} is bounded.

Note that the adjoint operator H^* is given by

$$H^* : L_2(0, T; Y) \rightarrow X, \quad H^* y(\cdot) = \int_0^T S^*(t) \Pi^* y(t) dt.$$

This gives that the system (2) is continuously initially observable iff the dual system is exactly controllable.

It is well known that a necessary condition of exact controllability is that the corresponding semigroup is onto for all $t \geq 0$ (cf. for example [5, 6, 7]). That is a necessary condition of continuous initial observability is that the operators $S^*(t)$ are onto. Hence, the system (2) can never be continuously initially observable if the semigroup $S(t)$ is analytical or compact in an infinite dimensional Hilbert space. The assumptions in the main result of [1] are contradictory.

References

- [1] Jae Rong Choi, Young Chel Kwun, Jong Seo Park, Continuous initial observability of nonlinear delay parabolic equations, Far East J. Appl. Math **10**(1) (2003), 15–28.
- [2] N. Carmichael, A. J. Pritchard, M. D. Quinn, State parameter estimation for nonlinear systems, Appl. Math. Optim. **9** (1982), 133–161.
- [3] M. D. Quinn, N. Carmichael, An approach to non-linear control problem using fixed-point methods, degree theory and pseudo-inverses. Numer. Funct. Anal. and Optimiz, **7**(2&3)(1984-85), 197–219.
- [4] R. F. Curtain, H. Zwart, An introduction to infinite dimensional linear systems theory, Springer, New York, 1995.
- [5] J. C. Louis, D. Wexler, On exact controllability in Hilbert space, J. Diff. Equat. **49** (1983), 258–269.
- [6] R. Rabah, Commandabilité des systèmes linéaires à retard constant dans les espaces de Banach. RAIRO-APII **20** (1986), 529–539.
- [7] R. Rabah, J. Karrakchou, Exact controllability and complete stabilizability for linear systems in Hilbert spaces, Appl. Math. Lett. **10** (1997), 35–40.